


# ACTUADOR ELÉCTRICO MULTIVOLTAJE


## J3 CONSUMO / CONSUMPTION

A PAR MÁXIMO +/- 5% / AT MAXIMUM TORQUE +/- 5%


|                | VOLTAJE (V) / VOLTAGE (V)<br>L = 12 - 24 VAC / VDC                                                                                        | VOLTAJE (V) / VOLTAGE (V)<br>H= 85 - 240 VAC / VDC<br>50/60 Hz                                                                           | TIEMPO MANIOBRA (Seg.) /<br>WORKING TIME (Sec.)                      |
|----------------|-------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------|
| <b>J3 - 20</b> | 12 VAC 1806 mA - <b>21,7 W</b><br>12 VDC 2131,5 mA - <b>25,6 W</b><br>24 VAC 787,5 mA - <b>18,9 W</b><br>24 VDC 913,5 mA - <b>21,9 W</b>  | 110 VAC 168 mA - <b>18,5 W</b><br>110 VDC 210 mA - <b>23,1 W</b><br>220 VAC 84 mA - <b>18,5 W</b><br>220 VDC 105 mA - <b>23,1 W</b>      | H = 11 seg. / <b>H = 11 sec.</b><br>L = 12 seg. / <b>L = 12 sec.</b> |
| <b>J3 - 35</b> | 12 VAC 2709 mA - <b>32,5 W</b><br>12 VDC 3234 mA - <b>38,8 W</b><br>24 VAC 1071 mA - <b>25,7 W</b><br>24 VDC 1491 mA - <b>35,8 W</b>      | 110 VAC 231 mA - <b>25,4 W</b><br>110 VDC 241,5 mA - <b>26,6 W</b><br>220 VAC 115,5 mA - <b>25,4 W</b><br>220 VDC 126 mA - <b>27,7 W</b> | H = 11 seg. / <b>H = 11 sec.</b><br>L = 12 seg. / <b>L = 12 sec.</b> |
| <b>J3 - 55</b> | 12 VAC 076,5 mA - <b>36,9 W</b><br>12 VDC 3181,5 mA - <b>38,2 W</b><br>24 VAC 1239 mA - <b>29,7 W</b><br>24 VDC 1428 mA - <b>34,3 W</b>   | 110 VAC 231 mA - <b>25,4 W</b><br>110 VDC 252 mA - <b>27,7 W</b><br>220 VAC 105 mA - <b>23,1 W</b><br>220 VDC 126 mA - <b>27,7 W</b>     | H = 14 seg. / <b>H = 14 sec.</b><br>L = 16 seg. / <b>L = 16 sec.</b> |
| <b>J3 - 85</b> | 12 VAC 2173,5 mA - <b>26,1 W</b><br>12 VDC 2698,5 mA - <b>32,4 W</b><br>24 VAC 934,5 mA - <b>22,4 W</b><br>24 VDC 1176 mA - <b>28,2 W</b> | 110 VAC 168 mA - <b>18,5 W</b><br>110 VDC 220,5 mA - <b>24,3 W</b><br>220 VAC 84 mA - <b>18,5 W</b><br>220 VDC 94,5 mA - <b>20,8 W</b>   | H = 30 seg. / <b>H = 30 sec.</b><br>L = 35 seg. / <b>L = 35 sec.</b> |




**J3 20**



**J3 35**



**J3 55/85**



**J3 140/300**